

ADDRESSABLE - Optical Smoke Beam Detector

Model 6500E and 6500SE

Overview

Features

- Unique servo-operated test filter
- Combined transmitter and receiver unit
- Range 10 – 70 meters, 70- 100 meters with long range kit
- 4 x fixed sensitivity/threshold levels
- 2 x automatic variable sensitivity modes
- Operates in the Infra-Red light spectrum
- Numerical indicators to aid beam alignment
- Standby, fault and alarm LED indicators visible from the front and bottom
- $\pm 10^\circ$ horizontal and vertical beam alignment
- Automatic drift compensation
- Uses the Series 200 plus protocol
- Loop powered
- CPR approved to EN54 – 12:2015
- Extended Warranty



Description

The 6500E and 6500SE are addressable reflector-type linear optical beam smoke detectors designed to operate as a component of an intelligent fire alarm system. They operate primarily on the principle of light obscuration utilising an Infra-Red beam. Optical beam smoke detectors are particularly appropriate for protecting buildings with large open spaces such as warehouses, atriums etc.

The 6500E and 6500SE detectors are combined transmitter/receiver units that can be directly connected to an analogue loop circuit. The Infra-Red transmitter generates a beam of light towards a high efficiency reflector. The reflector returns the beam to the receiver where an analysis of the received signal is made. The change in the strength of the received signal is used to determine the alarm condition. The 6500SE features a unique remote test capability that fully tests both the optics and the electronics of the device. An optical filter is automatically introduced in front of the optics, attenuating the returned beam and causing the unit to go into alarm.

Alignment of the detector is simplified with the aid of the detector's "gunsight" targeting device. Alignment of the detector with the reflector can then be "fine tuned" with the aid of a numerical signal strength indicator.

The sensitivity of the detector can be set to between 25% and 50% obscuration, providing application flexibility to suit the environment in which the detector will be installed. In addition to the four fixed value alarm thresholds, there are two variable thresholds that automatically compensate for changes in the environment which could otherwise result in unwanted alarms while remaining within a known sensitivity range.

The detector incorporates automatic drift compensation, whereby the detector will adjust its detection thresholds in line with any long term signal reduction of the beam caused by contamination of the optical surface.

The detector can be adjusted up to 10° vertically and horizontally for alignment. Where greater angular adjustment is required, the multi-mount accessory enables the detector to move through 28° vertically and 360° horizontally when ceiling mounted or up to 23° vertically and 90° horizontally when wall mounted.

All System Sensor products are covered by our extended 3 year warranty.

Architect/Engineer Specifications

6500E and 6500SE Conventional Optical Beam Smoke Detectors



Installation Recommendations

Installation should be undertaken in accordance with recognised national or international standards and codes of practice. The recommendations detailed in our "Application Guide for Projected Beam Smoke Detectors"(A05-0095) should also be taken into consideration.

We would also recommend that simulated fire tests are conducted to ensure that the desired response time for a given installation are met.

Electrical Specifications

| | | |
|--------------------------------|--|---|
| Operating Voltage Range | 15 to 32VDC (24VDC nominal)* | 15 to 28.5VDC if using built-in isolators |
| Typical Standby Current | 2mA @ 24VDC (No communications, LED off) | |
| Maximum Alarm Current (LED on) | 8.5mA | |

Environmental Specifications

| | |
|-------------------------------|---|
| Application Temperature Range | -30°C to +55°C |
| Humidity | 0 to 95% Relative Humidity (non condensing) |
| IP Rating | IP54 |

Mechanical Information

| | |
|------------------------------|--|
| Height | 254mm, 6500-SMK backbox 230mm |
| Diameter | 84mm |
| Width | Detector 190mm, 6500-SMK backbox 178mm |
| Weight | 1.77kg |
| Max Wire Gauge for Terminals | 2.0mm ² |
| Colour | White trim, black box |
| Material | Trim - Bayblend FR110, Lens cover - Lexan, Backbox - Noryl |
| Reflector | 200 x 230mm (5 – 70m range, supplied as standard) |

Product Range

| | |
|-------------|---|
| Accessories | |
| 6500-LRK | Long Range reflector kit (70 – 100m range). 3 off 200 x 230mm. |
| 6500-MMK | Multi-mount accessory for ceiling or wall mounting with additional mounting adjustment. 6500-SMK also required |
| 6500-SMK | Surface Mount accessory |
| BEAMHK | Heater Kit for the beam |
| BEAMHKR | Heater Kit for the reflector |
| RTS151KEY | Reset and test station, flush mount |
| RTS151KIT | Reset and test station with surface mount back box |

*6500SE requires external 24V supply to operate Asuretest (Remote test capability)

System Sensor (Technical Services)

System Sensor Europe
Unit C2
Foundry Lane, Horsham, West Sussex
RH13 5YZ, UK
Tel: +44 (0)1403 330240
Fax: +44 (0)1403 330695
Email: sse.technical@systemsensoreurope.com
www.systemsensoreurope.com

System Sensor Europe (Customer Services)

Life Safety Distribution GmbH
Javastrasse 2, 8604 Hegnau
Switzerland
Tel: 0041 44 943 4400
Email: orders@systemsensoreurope.com
www.systemsensoreurope.com